

FCC Information and Copyright

This equipment has been tested and found to comply with the limits of a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. There is no guarantee that interference will not occur in a particular installation.

The vendor makes no representations or warranties with respect to the contents here and specially disclaims any implied warranties of merchantability or fitness for any purpose. Further the vendor reserves the right to revise this publication and to make changes to the contents here without obligation to notify any party beforehand.

Duplication of this publication, in part or in whole, is not allowed without first obtaining the vendor's approval in writing.

The content of this user's manual is subject to be changed without notice and we will not be responsible for any mistakes found in this user's manual. All the brand and product names are trademarks of their respective companies.



Dichiarazione di conformità sintetica

Ai sensi dell'art. 2 comma 3 del D.M. 275 del 30/10/2002

Si dichiara che questo prodotto è conforme alle normative vigenti e soddisfa i requisiti essenziali richiesti dalle direttive

2004/108/CE, 2006/95/CE e 1999/05/CE

quando ad esso applicabili

Short Declaration of conformity

We declare this product is complying with the laws in force and meeting all the essential requirements as specified by the directives

2004/108/CE, 2006/95/CE and 1999/05/CE

whenever these laws may be applied

Table of Contents

Chapter 1: Introduction	1
1.1 Before You Start.....	1
1.2 Package Checklist.....	1
1.3 Motherboard Specifications	2
1.4 Rear Panel Connectors	3
1.5 Motherboard Layout	4
Chapter 2: Hardware Installation	5
2.1 Install Central Processing Unit (CPU)	5
2.2 Install a Heatsink	6
2.3 Connect Cooling Fans	7
2.4 Install System Memory	8
2.5 Expansion Slots	10
2.6 Jumper Setting	11
2.7 Headers & Connectors	12
Chapter 3: UEFI BIOS & Software.....	18
3.1 UEFI BIOS Setup	18
3.2 BIOS Update	18
3.3 Software.....	23
Chapter 4: Useful Help	27
4.1 Driver Installation.....	27
4.2 AMI BIOS Beep Code.....	28
4.3 Troubleshooting	28
4.4 RAID Functions	30
4.5 AMD Dual Graphics Technology	32
Appendix: Specifications In Other Languages	34
Arabic	34
French	36
German.....	38
Italian	40
Japanese.....	42
Polish.....	44
Portuguese	46
Russian.....	48
Spanish.....	50

CHAPTER 1: INTRODUCTION

1.1 Before You Start

Thank you for choosing our product. Before you start installing the motherboard, please make sure you follow the instructions below:

- Prepare a dry and stable working environment with sufficient lighting.
- Always disconnect the computer from power outlet before operation.
- Before you take the motherboard out from anti-static bag, ground yourself properly by touching any safely grounded appliance, or use grounded wrist strap to remove the static charge.
- Avoid touching the components on motherboard or the rear side of the board unless necessary. Hold the board on the edge, do not try to bend or flex the board.
- Do not leave any unfastened small parts inside the case after installation. Loose parts will cause short circuits which may damage the equipment.
- Keep the computer from dangerous area, such as heat source, humid air and water.
- The operating temperatures of the computer should be 0 to 45 degrees Celsius.
- To avoid injury, be careful of:
Sharp pins on headers and connectors
Rough edges and sharp corners on the chassis
Damage to wires that could cause a short circuit

1.2 Package Checklist


- Serial ATA Cable x2
- Rear I/O Panel for ATX Case x1
- User's Manual x1
- Fully Setup Driver DVD x1

<p>Note: The package contents may be different due to the sales region or models in which it was sold. For more information about the standard package in your region, please contact your dealer or sales representative.</p>

1.3 Motherboard Specifications

Specifications																															
CPU Support	Socket FM2+/FM2 for AMD A-series processor Maximum CPU TDP (Thermal Design Power): 100Watt * Please refer to www.biostar.com.tw for CPU support list.																														
Chipset	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)																														
Memory	Supports Dual Channel DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) 2 x DDR3 DIMM Memory Slot, Max. Supports up to 32 GB Memory Each DIMM supports non-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3 module * Please refer to www.biostar.com.tw for Memory support list.																														
Storage	AMD A88X/A78 FCH Supports RAID 0,1,10, 5 & AHCI (AMD A88X FCH) Supports RAID 0,1,10, & AHCI (AMD A78 FCH),																														
LAN	Realtek RTL 8111G 10/ 100/ 1000 Mb/s auto negotiation, Half / Full duplex capability																														
Audio Codec	ALC892 7.1 Channels, High Definition Audio (2-channel output is from front audio header)																														
USB	AMD A88X/A78 FCH: 6x USB 2.0 port (2 on rear I/Os and 4 via internal headers) 4x USB 3.0 port (2 on rear I/Os and 2 via internal headers)																														
Expansion Slots	2x PCI Slot 1x PCIe 2.0 x1 Slot 1x PCIe 3.0 x16 Slot (Only FM2+ processors can support PCIe 3.0.)																														
Rear I/Os	1x PS/2 Mouse 1x PS/2 Keyboard 1x HDMI Port 1x VGA Port 1x DVI Port 1x LAN port 2x USB 2.0 Port 2x USB 3.0 Port 3x Audio Jack																														
Internal I/Os	<table border="0"> <tr> <td>Hi-Fi A88S3E:</td> <td>Hi-Fi A78S3E:</td> </tr> <tr> <td>8x SATA 6.0Gb/s Connector</td> <td>6x SATA 6.0Gb/s Connector</td> </tr> <tr> <td>2x USB 2.0 Header</td> <td>2x USB 2.0 Header</td> </tr> <tr> <td>1x USB 3.0 Header</td> <td>1x USB 3.0 Header</td> </tr> <tr> <td>1x 4-Pin Power Connector</td> <td>1x 4-Pin Power Connector</td> </tr> <tr> <td>1x 24-Pin Power Connector</td> <td>1x 24-Pin Power Connector</td> </tr> <tr> <td>1x CPU Fan Connector</td> <td>1x CPU Fan Connector</td> </tr> <tr> <td>2x System Fan Connector</td> <td>2x System Fan Connector</td> </tr> <tr> <td>1x Front Panel Header</td> <td>1x Front Panel Header</td> </tr> <tr> <td>1x Front Audio Header</td> <td>1x Front Audio Header</td> </tr> <tr> <td>1x Clear CMOS Header</td> <td>1x Clear CMOS Header</td> </tr> <tr> <td>1x Printer Port Header</td> <td>1x Printer Port Header</td> </tr> <tr> <td>1x Serial Port Header</td> <td>1x Serial Port Header</td> </tr> <tr> <td>1x S/PDIF out Connector</td> <td>1x S/PDIF out Connector</td> </tr> <tr> <td>1x Consumer IR Header</td> <td>1x Consumer IR Header</td> </tr> </table>	Hi-Fi A88S3E:	Hi-Fi A78S3E:	8x SATA 6.0Gb/s Connector	6x SATA 6.0Gb/s Connector	2x USB 2.0 Header	2x USB 2.0 Header	1x USB 3.0 Header	1x USB 3.0 Header	1x 4-Pin Power Connector	1x 4-Pin Power Connector	1x 24-Pin Power Connector	1x 24-Pin Power Connector	1x CPU Fan Connector	1x CPU Fan Connector	2x System Fan Connector	2x System Fan Connector	1x Front Panel Header	1x Front Panel Header	1x Front Audio Header	1x Front Audio Header	1x Clear CMOS Header	1x Clear CMOS Header	1x Printer Port Header	1x Printer Port Header	1x Serial Port Header	1x Serial Port Header	1x S/PDIF out Connector	1x S/PDIF out Connector	1x Consumer IR Header	1x Consumer IR Header
Hi-Fi A88S3E:	Hi-Fi A78S3E:																														
8x SATA 6.0Gb/s Connector	6x SATA 6.0Gb/s Connector																														
2x USB 2.0 Header	2x USB 2.0 Header																														
1x USB 3.0 Header	1x USB 3.0 Header																														
1x 4-Pin Power Connector	1x 4-Pin Power Connector																														
1x 24-Pin Power Connector	1x 24-Pin Power Connector																														
1x CPU Fan Connector	1x CPU Fan Connector																														
2x System Fan Connector	2x System Fan Connector																														
1x Front Panel Header	1x Front Panel Header																														
1x Front Audio Header	1x Front Audio Header																														
1x Clear CMOS Header	1x Clear CMOS Header																														
1x Printer Port Header	1x Printer Port Header																														
1x Serial Port Header	1x Serial Port Header																														
1x S/PDIF out Connector	1x S/PDIF out Connector																														
1x Consumer IR Header	1x Consumer IR Header																														
Form Factor	microATX Form Factor, 244 mm x 200 mm																														
OS Support	Windows XP / 7 / 8 Biostar reserves the right to add or remove support for any OS with or without notice.																														

1.4 Rear Panel Connectors



- Note 1:** HDMI / DVI-D / VGA Output require an AMD family processor with integrated graphics.
- Note 2:** The mainboard supports three independent display outputs.
- Note 3:** Since the audio chip supports High Definition Audio Specification, the function of each audio jack can be defined by software. The input / output function of each audio jack listed above represents the default setting. However, when connecting external microphone to the audio port, please use the Line In (Blue) and Mic In (Pink) audio jack.

Note 4: Maximum resolution:


Outputs	Maximum resolution	Bit Depth
HDMI	1920 x 1080 @60Hz	24, 30, 36 bpp
	1920 x 1200 @60Hz	24 bpp
DVI-D	1920 x 1200 @60Hz	30 bpp
	2560 x 1600 @60Hz	24 bpp
VGA	1920 x 1600 @60Hz	--

Note 5: To configure 7.1-channel audio, you have to use a chassis with HD front panel audio module and enable the multi-channel audio feature through O.S. Audio Utility.

The 2 / 4 / 5.1/7.1-channel configuration

Port	2-channel	4-channel	5.1 channel	7.1 channel
Blue (Rear Panel)	Line In	Rear Speaker Out	Rear Speaker Out	Rear Speaker Out
Green (Rear Panel)	Line Out	Front Speaker Out	Front Speaker Out	Front Speaker Out
Pink (Rear Panel)	Mic In	Mic In	Center/Subwoofer Out	Center/Subwoofer Out
Green (Front Panel)	--	--	--	Side Speaker Out

1.5 Motherboard Layout




Note1: ■ represents the 1st pin.


CHAPTER 2: HARDWARE INSTALLATION

2.1 Install Central Processing Unit (CPU)


Step 1: Locate the CPU socket on the motherboard



Step 2: Pull the socket locking out from the socket and then raise the lever up to a 90-degree angle.




Step 3: Look for the white triangle on socket, and the gold triangle on CPU should point towards this white triangle. The CPU will fit only in the correct orientation.




Motherboard Manual

Step 4: Hold the CPU down firmly, and then close the lever to locked the position



2.2 Install a Heatsink

Step 1: Place the heatsink and fan assembly onto the retention frame. Match the heatsink clip with the socket mounting-lug. Hook the spring clip to the mounting-lug.



Step 2: On the other side, push the retention clip straight down to lock into the plastic lug on the retention frame, and then press down the locker until it stops.




Note1: Do not forget to connect the CPU fan connector.

Note2: For proper installation, please kindly refer to the installation manual of your CPU heatsink.

2.3 Connect Cooling Fans


These fan headers support cooling-fans built in the computer. The fan cable and connector may be different according to the fan manufacturer. Connect the fan cable to the connector while matching the black wire to pin#1.

CPU_FAN1: CPU Fan Header



Pin	Assignment
1	Ground
2	+12V
3	FAN RPM rate sense
4	Smart Fan Control (By Fan)

SYS_FAN1/2: System Fan Header




Pin	Assignment
1	Ground
2	+12V
3	FAN RPM rate sense


Note: CPU_FAN1, SYS_FAN1/2 support 4-pin and 3-pin head connectors. When connecting with wires onto connectors, please note that the red wire is the positive and should be connected to pin#2, and the black wire is Ground and should be connected to GND.

2.4 Install System Memory


A. DDR3 Modules



Step 1: Unlock a DIMM slot by pressing the retaining clips outward. Align a DIMM on the slot such that the notch on the DIMM matches the break on the slot.



Step 2: Insert the DIMM vertically and firmly into the slot until the retaining clips snap back in place and the DIMM is properly seated.



Note: If the DIMM does not go in smoothly, do not force it. Pull it all the way out and try again.

B. Memory Capacity

DIMM Socket Location	DDR3 Module	Total Memory Size
DDR3_A1	512MB/1GB/2GB/4GB/8GB/16GB	Max is 32GB.
DDR3_B1	512MB/1GB/2GB/4GB/8GB/16GB	

C. Dual Channel Memory Installation


Please refer to the following requirements to activate Dual Channel function:
Install memory module of the same density in pairs, shown in the table.

Dual Channel Status	DDR3_A1	DDR3_B1
Disabled	O	X
Disabled	X	O
Enabled	O	O

(O means memory installed, X means memory not installed.)

Note: The DRAM bus width of the memory module must be the same (x8 or x16)

2.5 Expansion Slots



PEX16_1: PCI-Express Gen3 x16 Slot

- PCI-Express 3.0 compliant.
- Maximum theoretical realized bandwidth of 16GB/s simultaneously per direction, for an aggregate of 32GB/s totally.
- Only FM2+ processors can support PCIe 3.0.

PEX1_1: PCI-Express Gen2 x1 Slot

- PCI-Express 2.0 compliant.
- Data transfer bandwidth up to 500MB/s per direction; 1GB/s in total

PCI1/PCI2: Peripheral Component Interconnect Slot

This motherboard is equipped with 1 standard PCI slot. PCI stands for Peripheral Component Interconnect, and it is a bus standard for expansion cards.

Install an Expansion Card

You can install your expansion card by following steps:

1. Read the related expansion card's instruction document before install the expansion card into the computer.
2. Remove your computer's chassis cover, screws and slot bracket from the computer.
3. Place a card in the expansion slot and press down on the card until it is completely seated in the slot.
4. Secure the card's metal bracket to the chassis back panel with a screw.
5. Replace your computer's chassis cover.
6. Power on the computer, if necessary, change BIOS settings for the expansion card.
7. Install related driver for the expansion card.


2.6 Jumper Setting

The illustration shows how to set up jumpers. When the jumper cap is placed on pins, the jumper is “close”, if not, that means the jumper is “open”.



JCMOS1: Clear CMOS Header

Placing the jumper on pin2-3, it allows user to restore the BIOS safe setting and the CMOS data. Please carefully follow the procedures to avoid damaging the motherboard.




※ Clear CMOS Procedures:

1. Remove AC power line.
2. Set the jumper to “Pin 2-3 close”.
3. Wait for five seconds.
4. Set the jumper to “Pin 1-2 close”.
5. Power on the AC.
6. Load Optimal Defaults and save settings in CMOS.

2.7 Headers & Connectors

ATXPWR1: ATX Power Source Connector


For better compatibility, we recommend to use a standard ATX 24-pin power supply for this connector. Make sure to find the correct orientation before plugging the connector.



Pin	Assignment	Pin	Assignment
13	+3.3V	1	+3.3V
14	-12V	2	+3.3V
15	Ground	3	Ground
16	PS_ON	4	+5V
17	Ground	5	Ground
18	Ground	6	+5V
19	Ground	7	Ground
20	NC	8	PW_OK
21	+5V	9	Standby Voltage+5V
22	+5V	10	+12V
23	+5V	11	+12V
24	Ground	12	+3.3V

ATXPWR2: ATX Power Source Connector

This connector will provide +12V to CPU power circuit.




Pin	Assignment
1	+12V
2	+12V
3	Ground
4	Ground

Note1: Before you power on the system, please make sure that both ATXPWR1 and ATXPWR2 connectors have been plugged-in.

Note2: Insufficient power supplied to the system may result in instability or the peripherals not functioning properly. Use of a PSU with a higher power output is recommended when configuring a system with more power-consuming devices.

PANEL1: Front Panel Header

This 16-pin connector includes Power-on, Reset, HDD LED, Power LED, and speaker connection. It allows user to connect the PC case's front panel switch functions.




Pin	Assignment	Function	Pin	Assignment	Function
1	+5V	Speaker Connector	9	N/A	N/A
2	N/A		10	N/A	
3	N/A		11	N/A	
4	Speaker		12	Power LED (+)	Power LED
5	HDD LED (+)	Hard drive LED	13	Power LED (+)	
6	HDD LED (-)		14	Power LED (-)	
7	Ground	Reset button	15	Power button	Power-on button
8	Reset control		16	Ground	

SATA1~SATA6: Serial ATA Connectors


These connectors connect to SATA hard disk drives via SATA cables.

- Hi-Fi A88S3E & Hi-Fi A78S3E satisfy the SATA 3.0 spec and with transfer rate of 6.0Gb/s.
- SATA6 is only for Hi-Fi A88S3E.



JFRONT_USB3_1: Header for USB 3.0 Ports at Front Panel


This header allows user to connect additional USB cable on the PC front panel, and also can be connected with a wide range of simultaneously accessible external Plug and Play peripherals.



Pin	Assignment	Pin	Assignment
1	VBUS0	11	D2+
2	SSRX1-	12	D2-
3	SSRX1+	13	Ground
4	Ground	14	SSTX2+
5	SSTX1-	15	SSTX2-
6	SSTX1+	16	Ground
7	Ground	17	SSRX2+
8	D1-	18	SSRX2-
9	D1+	19	VBUS1
10	ID	20	Key

F_USB1/F_USB2: Headers for USB 2.0 Ports at Front Panel


This header allows user to connect additional USB cable on the PC front panel, and also can be connected with a wide range of simultaneously accessible external Plug and Play peripherals.



Pin	Assignment
1	+5V (fused)
2	+5V (fused)
3	USB-
4	USB-
5	USB+
6	USB+
7	Ground
8	Ground
9	NC
10	Key

F_AUDIO1: Front Panel Audio Header

This header allows user to connect the front audio output cable with the PC front panel. This header supports HD and AC'97 audio front panel connector.




HD Audio		AC'97	
Pin	Assignment	Pin	Assignment
1	Mic Left in	1	Mic In
2	Ground	2	Ground
3	Mic Right in	3	Mic Power
4	GPIO	4	Audio Power
5	Right line in	5	RT Line Out
6	Jack Sense	6	RT Line Out
7	Front Sense	7	Reserved
8	Key	8	Key
9	Left line in	9	LFT Line Out
10	Jack Sense	10	LFT Line Out

Note1: It is recommended that you connect a high-definition front panel audio module to this connector to avail of the motherboard's high definition audio capability.

Note2: Please try to disable the "Front Panel Jack Detection" if you want to use an AC'97 front audio output cable. The function can be found via O.S. Audio Utility.

J_COM1: Serial Port Connector


The motherboard has a Serial Port Connector for connecting RS-232 Port.



Pin	Assignment
1	Carrier detect
2	Received data
3	Transmitted data
4	Data terminal ready
5	Signal ground
6	Data set ready
7	Request to send
8	Clear to send
9	Ring indicator
10	NC

J_PRINT1: Printer Port Connector


This header allows you to connect printer on the PC.



Pin	Assignment	Pin	Assignment
1	-Strobe	14	Ground
2	-ALF	15	Data 6
3	Data 0	16	Ground
4	-Error	17	Data 7
5	Data 1	18	Ground
6	-Init	19	-ACK
7	Data 2	20	Ground
8	-Scltin	21	Busy
9	Data 3	22	Ground
10	Ground	23	PE
11	Data 4	24	Ground
12	Ground	25	SCLT
13	Data 5	26	Key

JSPDIFOUT1: Digital Audio-out Connectors


The JSPDIFOUT1 is for connecting the PCI bracket SPDIF output.



Pin	Assignment
1	+5V
2	SPDIF_OUT
3	Ground

CIR1: Consumer IR Connector

This header is for infrared remote control and communication.



Pin	Assignment
1	IrDA serial input
2	Ground
3	Ground
4	Key
5	IrDA serial output
6	IR Power

CHAPTER 3: UEFI BIOS & SOFTWARE

3.1 UEFI BIOS Setup

- For better system performance, the UEFI BIOS firmware is being continuously updated. The UEFI BIOS information described below in this manual is for your reference only and the actual UEFI BIOS information and settings on board may be different from this manual
- For further information of setting up the UEFI BIOS, please refer to the UEFI BIOS Manual in the Setup DVD.

3.2 BIOS Update

There are three ways to update the BIOS:
BIOS Update Utility, BIOS Online Update Utility and BIOS Flasher.


1. BIOS Update Utility

1. Installing BIOS Update Utility from the DVD Driver.
2. Download the proper BIOS from www.biostar.com.tw .


3. Open BIOS Update Utility and click the **Update BIOS** button on the main screen.




4. A warning message will show up to request your agreement to start the BIOS update. Click **OK** to start the update procedure.



5. Choose the location for your BIOS file in the system. Please select the proper BIOS file, and then click on **Open**. It will take several minutes, please be patient.



6. After the BIOS Update process is finished, click on **OK** to reboot the system.




7. While the system boots up and the full screen logo shows up, please press the **Del** <Delete> key to enter BIOS setup.

After entering the BIOS setup, please go to the **Save & Exit**, using the **Restore Defaults** function to load Optimized Defaults, and select **Save Changes and Reset** to restart the computer. Then, the BIOS Update is completed.

Backup BIOS

Click the Backup BIOS button on the main screen for the backup of BIOS, and select a proper location for your backup BIOS file in the system, and click **Save**.




2. Online Update Utility

1. Installing BIOS Update Utility from the DVD Driver.
2. Please make sure the system is connected to the internet before using this function.


3. Open BIOS Update Utility and click the **Online Update** button on the main screen.




4. An open dialog will show up to request your agreement to start the BIOS update. Click **Yes** to start the online update procedure.




5. If there is a new BIOS version, the utility will ask you to download it. Click **Yes** to proceed.




6. After the download is completed, you will be asked to program (update) the BIOS or not. Click **Yes** to proceed.



7. After the updating process is finished, you will be asked you to reboot the system. Click **OK** to reboot.



8. While the system boots up and the full screen logo shows up, press  <Delete> key to enter BIOS setup.

After entering the BIOS setup, please go to the **Save & Exit**, using the **Restore Defaults** function to load Optimized Defaults, and select **Save Changes and Reset** to restart the computer. Then, the BIOS Update is completed.

3. BIOSTAR BIOS Flasher

BIOSTAR BIOS Flasher is a BIOS flashing utility providing you an easy and simple way to update your BIOS via USB pen drive.

Note1: This utility only allows storage device with FAT32/16 format and single partition.

Note2: Shutting down or resetting the system while updating the BIOS will lead to system boot failure.

The BIOSTAR BIOS Flasher is built in the BIOS ROM. To enter the utility, **press <F12> during the Power-On Self Tests (POST) procedure** while booting up.

Updating BIOS with BIOSTAR BIOS Flasher

1. Go to the website to download the latest BIOS file for the motherboard.
2. Then, copy and save the BIOS file into a USB flash (pen) drive.
3. Insert the USB pen drive that contains the BIOS file to the USB port.
4. Power on or reset the computer and then press **<F12>** during the **POST** process.


5. After entering the POST screen, the BIOS-FLASHER utility pops out. Choose [fs0] to search for the BIOS file.




6. Select the proper BIOS file, and a message asking if you are sure to flash the BIOS file. Click Yes to start updating BIOS.



7. A dialog pops out after BIOS flash is completed, asking you to restart the system. Press the [Y] key to restart system.



8. While the system boots up and the full screen logo shows up, press  <Delete> key to enter BIOS setup.

After entering the BIOS setup, please go to the **Save & Exit**, using the **Restore Defaults** function to load Optimized Defaults, and select **Save Changes and Reset** to restart the computer. Then, the BIOS Update is completed.

3.3 Software

Installing Software

1. Insert the Setup DVD to the optical drive. The driver installation program would appear if the Autorun function has been enabled.
2. Select **Software Installation**, and then click on the respective software title.
3. Follow the on-screen instructions to complete the installation.

Note1: All the information and content about following software are subject to be changed without notice. For better performance, the software is being continuously updated.

Note2: The information and pictures described below are for your reference only. The actual information and settings on board may be slightly different from this manual.

Launching Software

After the installation process is completed, you will see the software icon showing on the desktop. Double-click the icon to launch it.

eHot-Line

eHot-Line is a convenient utility that helps you to contact with our Tech-Support system. This utility will collect the system information which is useful for analyzing the problem you may have encountered, and then send these information to our tech-support department to help you fix the problem.

Note: Before you use this utility, please set Outlook Express as your default e-mail client application program.

*represents important information that you must provide. Without this information, you may not be able to send out the mail.

This block will show the information which would be collected in the mail.

*Describe condition of your system.

*Select your area or the area close to you.

Provide the e-mail address that you would like to send the copy to.

*Provide the name of the memory module manufacturer.

Provide the name of the power supply manufacturer and the model no.

Send the mail out.


Exit this dialog.

Save these information to a .txt file

The screenshot shows the eHot-Line utility window. On the left, there is a list of system information under 'Base board information'. On the right, there is a 'Symptom Description' text area. Below these are several input fields: 'Region', 'CC E-mail', 'Memory Module Manufacture', and 'Power Supply Manufacture/model'. At the bottom, there are three buttons: 'Send', 'Save As...', and 'Exit'. Red arrows point from text annotations to various parts of the interface, highlighting important fields and buttons.


Motherboard Manual

After filling up this information, click **“Send”** to send the mail out. A warning dialog would appear asking for your confirmation; click **“Send”** to confirm or **“Do Not Send”** to cancel.




If you want to save this information to a .txt file, click **“Save As...”** and then you will see a saving dialog appears asking you to enter file name.

Enter the file name and then click **“Save”**. Your system information will be saved to a .txt file.




Open the saved .txt file, you will see your system information including motherboard/BIOS/CPU/video/device/OS information. This information is also concluded in the sent mail.



Note1: We will not share customer's data with any other third parties, so please feel free to provide your system information while using eHot-Line service.
Note2: If you are not using Outlook Express as your default e-mail client application, you may need to save the system information to a .txt file and send the file to our tech support with other e-mail application. Go to the following web <http://www.biostar.com.tw/app/en/about/contact.php> for getting our contact information.

BIOScreen Utility

This utility allows you to personalize your boot logo easily. You can choose BMP as your boot logo so as to customize your computer.




Please follow the step-by-step instructions below to update boot logo:

- Load Image : Choose the picture as the boot logo.
- Transform : Transform the picture for BIOS and preview the result.
- Update Bios : Write the picture to BIOS Memory to complete the update.

Smart EAR

Smart EAR is a windows-based audio utility which allows you to easily adjust system volume. With its user-friendly GUI, you can also adjust impedance setting (Low/High Gain) to optimize your headphone performance.



- **High/Low Gain Switch:** Keep the gain switch to low for low impedance headphone and set to high for high impedance headphone.
- **Mute Button:** To disable system sound
- **Volume Control Knob:** The volume can be finely adjusted by turning the knob either clockwise or anti-clockwise to increase or decrease system volume accordingly.
- **Information Button:** Get information of the application
- **Minimize Button:** Minimize the application window to the taskbar
- **Exit Button:** Exit the application

Note:

1. Smart EAR is only supported by Windows 7/8 and BIOSTAR Hi-Fi series motherboards.
2. High/Low Gain Switch is only for "Front Panel Audio Header", please make sure you are connecting your headphone to the front panel I/O.

CHAPTER 4: USEFUL HELP

4.1 Driver Installation

After you installed your operating system, please insert the Fully Setup Driver DVD into your optical drive and install the driver for better system performance.

You will see the following window after you insert the DVD



The setup guide will auto detect your motherboard and operating system.

Note: If this window didn't show up after you insert the Driver DVD, please use file browser to locate and execute the file SETUP.EXE under your optical drive.

A. Driver Installation

To install the driver, please click on the Driver icon. The setup guide will list the compatible driver for your motherboard and operating system. Click on each device driver to launch the installation program.

B. Software Installation

To install the software, please click on the Software icon. The setup guide will list the software available for your system, click on each software title to launch the installation program.

C. Manual

Aside from the paperback manual, we also provide manual in the Driver DVD. Click on the Manual icon to browse for available manual.

Note: You will need Acrobat Reader to open the manual file. Please download the latest version of Acrobat Reader software from <http://get.adobe.com/reader/>

4.2 AMI BIOS Beep Code

Boot Block Beep Codes

Number of Beeps	Description
Continuing	Memory sizing error or Memory module not found

POST BIOS Beep Codes

Number of Beeps	Description
1	Success booting.
8	Display memory error (system video adapter)

4.3 Troubleshooting

Probable	Solution
<ol style="list-style-type: none"> There is no power in the system. Power LED does not shine; the fan of the power supply does not work Indicator light on keyboard does not shine. 	<ol style="list-style-type: none"> Make sure power cable is securely plugged in. Replace cable. Contact technical support.
System is inoperative. Keyboard lights are on, power indicator lights are lit, and hard drives are running.	Using even pressure on both ends of the DIMM, press down firmly until the module snaps into place.
System does not boot from a hard disk drive, but can be booted from optical drive.	<ol style="list-style-type: none"> Check cable running from disk to disk controller board. Make sure both ends are securely plugged in; check the drive type in the standard CMOS setup. Backing up the hard drive is extremely important. All hard disks are capable of breaking down at any time.
System only boots from an optical drive. Hard disks can be read, applications can be used, but system fails to boot from a hard disk.	<ol style="list-style-type: none"> Back up data and applications files. Reformat the hard drive. Re-install applications and data using backup disks.
Screen message shows "Invalid Configuration" or "CMOS Failure."	Review system's equipment. Make sure correct information is in setup.
System cannot boot after user installs a second hard drive.	<ol style="list-style-type: none"> Set master/slave jumpers correctly. Run SETUP program and select correct drive types. Call the drive manufacturers for compatibility with other drives.

CPU Overheated

If the system shutdown automatically after power on system for seconds, that means the CPU protection function has been activated.

When the CPU is over heated, the motherboard will shutdown automatically to avoid a damage of the CPU, and the system may not power on again.

In this case, please double check:

1. The CPU cooler surface is placed evenly with the CPU surface.
2. CPU fan is rotated normally.
3. CPU fan speed is fulfilling with the CPU speed.

After confirmed, please follow steps below to relief the CPU protection function.

1. Remove the power cord from power supply for seconds.
2. Wait for seconds.
3. Plug in the power cord and boot up the system.


Or you can:

1. Clear the CMOS data.
(See "Close CMOS Header: JCMOS1" section)
2. Wait for seconds.
3. Power on the system again.

4.4 RAID Functions

RAID Definitions

RAID 0:




In a RAID 0 system data are split up in blocks that get written across all the drives in the array. By using multiple disks (at least 2) at the same time, this offers superior I/O performance. This performance can be enhanced further by using multiple controllers, ideally one controller per disk.

Features and Benefits

- **Drives:** Minimum 2, and maximum is up to 6 or 8. Depending on the platform.
- **Uses:** Intended for non-critical data requiring high data throughput, or any environment that does not require fault tolerance.
- **Benefits:** provides increased data throughput, especially for large files. No capacity loss penalty for parity.
- **Drawbacks:** Does not deliver any fault tolerance. If any drive in the array fails, all data is lost.
- **Fault Tolerance:** No.
- **Total Capacity:** (Minimal. HDD Capacity) x (Connected HDDs Amount)

RAID 1:




Data are stored twice by writing them to both the data disk (or set of data disks) and a mirror disk (or set of disks). If a disk fails, the controller uses either the data drive or the mirror drive for data recovery and continues operation. You need at least 2 disks for a RAID 1 array.

Features and Benefits

- **Drives:** Minimum 2, and maximum is 2.
- **Uses:** RAID 1 is ideal for small databases or any other application that requires fault tolerance and minimal capacity.
- **Benefits:** Provides 100% data redundancy. Should one drive fail, the controller switches to the other drive.
- **Drawbacks:** Requires 2 drives for the storage space of one drive. Performance is impaired during drive rebuilds.
- **Fault Tolerance:** Yes.

RAID 10:




RAID 10 combines the advantages (and disadvantages) of RAID 0 and RAID 1 in one single system. It provides security by mirroring all data on a secondary set of disks (disk 3 and 4 in the drawing below) while using striping across each set of disks to speed up data transfers.

Features and Benefits

- **Drives:** Minimum 4, and maximum is 6 or 8, depending on the platform.
- **Benefits:** Optimizes for both fault tolerance and performance, allowing for automatic redundancy. May be simultaneously used with other RAID levels in an array, and allows for spare disks.
- **Drawbacks:** Requires twice the available disk space for data redundancy, the same as RAID level 1.
- **Fault Tolerance:** Yes.

RAID 5:



A RAID 5 array can withstand a single disk failure without losing data or access to data. Although RAID 5 can be achieved in software, a hardware controller is recommended. Often extra cache memory is used on these controllers to improve the write performance.

Features and Benefits

- **Drives:** Minimum 3.
- **Uses:** RAID 5 is recommended for transaction processing and general purpose service.
- **Benefits:** An ideal combination of good performance, good fault tolerance, and high capacity and storage efficiency.
- **Drawbacks:** Individual block data transfer rate same as a single disk. Write performance can be CPU intensive.
- **Fault Tolerance:** Yes.

Note: The RAID 5 function is only supported by A88X chip set.

4.5 AMD Dual Graphics Technology

AMD Dual Graphics Technology Introduction

When user adds a AMD PCIe display adapter, it can be integrated with IGD to show better performance. To make the two video devices work simultaneously and normally, please refer to the following setting.

AMD Dual Graphics Requirement

- Operating System: Windows 7 / Windows 8
- Supported Dual Graphics Combinations:

Richland APUs			
AMD Radeon™ Graphics Card	A10-Series HD 8670D	A8-Series HD8570D	A6-Series HD 8470D
"Oland" XT, HD 8870	●	●	●(Note2)
"Oland" Pro, HD 8850	●	●	●
"Turks" XT, HD 6670	●	●	●
"Turks" Pro, HD 6570	●	●	●
"Caicos" Pro, HD 6450	●	●	●
Trinity APUs			
AMD Radeon™ Graphics Card	A10-Series HD 7660D	A8-Series HD7560D	A6-Series HD 7540D
"Turks" XT, HD 6670	●	●	--
"Turks" Pro, HD 6570	●	●	●
"Caicos" Pro, HD 6450	--	--	●

● Recommended graphics cards for AMD dual-graphics

Note 1: A4-Series CPUs do not support Dual Graphics.


Note 2: Only available for DDR3 graphics memory

Note 3: The information described above in this manual is for your reference only and the actual information and settings on board may be different from this manual. For further AMD Dual Graphics information, please visit the following website: <http://www.amd.com>


AMD Dual Graphics Setup

Step 1: Insert Dual Graphics-Ready graphics card into PEX16_1 slot.

Step 2: Set the BIOS setting as follows:
 [Chipset]→[North Bridge]→[GFX Configuration]
 →[Surround View]→[Enabled]



Step 3: Install Driver DVD Chipset Driver, and reboot the system. Activate AMD VISION Engine Control Center to make sure CrossFire has been enabled.



APPENDIX: Specifications In Other Languages**Arabic**

المواصفات	
المأخذ FM2+/FM2 لمعالج ايه إم دي AMD تتسلسل A الحد الأقصى للطاقة الحرارية في تصميم المعالج (TDP – thermal design power) : 100 واط. * يرجى الرجوع إلى الموقع www.biostar.com.tw لقائمة دعم المعالج CPU.	قاعدة وحدة المعالجة المركزية
AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)	مجموعة الشرائح
تدعم قناة مزدوجة دي. دي. ار. DDR3 / 1600 / 1333 / 1066 / 800 / 2133 / 1866 / 1600 (OC) / 2400 (OC) X2 دي. دي. ار. DDR3 قنات الذاكرة المزدوجة DIMM، تتحمل كحد أقصى 32 جيجابايت ذاكرة كل فتحة مزدوجة DIMM تتحمل دون 512 ECC ميجا بايت 16/8/4/2/1/ جيجابايت دي. دي. ار. DDR3 * يرجى الرجوع إلى الموقع www.biostar.com.tw لقائمة دعم الذاكرة.	الذاكرة
ايه إم دي AMD A88X/A78 FCH تتحمّل رايد RAID 5 / 0 / 1 / 10 / IAHC (A88X FCH) تتحمّل رايد RAID 0 / 1 / 10 / AHCI (A78 FCH)	التخزين
ريالتيك رت ل REALTEK RTL 8111G 1000 / 100 / 10 ميجابايت / الثانية ، تحديد تلقائي ، النصف / القدرة القصوى المزدوجة	شبكة محلية LAN
ALC892 7.1 قنوات عالية النقة	الترميز الصوتي
يه إم دي AMD A88X/A78 FCH منفذ 6 x نقل متسلسل عام USB 2.0 (2 في المنافذ والمخارج الخلفية و 4 من خلال الموزع الداخلي) منفذ 4 x نقل متسلسل عام USB 3.0 (2 في المنافذ والمخارج الخلفية و 2 من خلال الموزع الداخلي)	نقل متسلسل عام USB
2 x فتحة منفذ الملحقات الإضافية PCI 1 x فتحة منفذ الملحقات الإضافية PCIe 2.0 x 1 1 x فتحة منفذ الملحقات الإضافية PCIe 3.0 x 16	فتحات التوسع
1 x PS/2 لفرة 1 x PS/2 لوحة المفاتيح للكمبيوتر قحة توصيل عدد 1 x HDMI وسيط متعدد العلي الوضوح قحة توصيل عدد 1 x منظومة العرض المرئي VGA قحة توصيل عدد 1 x واجهة مرئية رقمية DVI قحة لتوصيل عدد 1 x الشبكة المحلية LAN قحة توصيل عدد 2 x نقل متسلسل عام USB 2.0 قحة توصيل عدد 2 x نقل متسلسل عام USB 3.0 قحة توصيل عدد 3 x جك الصوت	المدخل والمخارج الخلفية

Hi-Fi A88S3E / Hi-Fi A78S3E

المواصفات		
Hi-Fi A78S3E	Hi-Fi A88S3E	
وصلة 6 SATA x 6 جيجابايت / الثانية	وصلة 8 SATA x 6 جيجابايت / الثانية	
موزع 2x نقل متصل عام USB 2.0	موزع 2x نقل متصل عام USB 2.0	
موزع 1x نقل متصل عام USB 3.0	موزع 1x نقل متصل عام USB 3.0	
موصلة للطاقة 1 x 4 دبابيس	موصلة للطاقة 1 x 4 دبابيس	
وصلة للطاقة 1x 24 دبوس	وصلة للطاقة 1x 24 دبوس	
وصلة 1 x مروحة تبريد وحدة المعالجة المركزية	وصلة 1 x مروحة تبريد وحدة المعالجة المركزية	المدخل والمخارج الداخلية
وصلة 2x مراوح تبريد المنظومة	وصلة 2x مراوح تبريد المنظومة	
موزع 1 x اللوحة الامامية	موزع 1 x اللوحة الامامية	
موزع 1x الصوت الامامي	موزع 1x الصوت الامامي	
موزع 1x سيموس مباشر	موزع 1x سيموس مباشر	
موزع 1x قحة للطابعة	موزع 1x قحة للطابعة	
موزع 1x قحة تسلسلية	موزع 1x قحة تسلسلية	
وصلة 1x خارجية S/PDIF سوني فيليبس الواجهة الرقمية	وصلة 1x خارجية S/PDIF سوني فيليبس الواجهة الرقمية	
موزع 1 x مستهلك IR	موزع 1 x مستهلك IR	
عامل شكل مدد التكنولوجيا المتقدمة microATX ، 244 مم x 200 مم		عامل الشكل
ويندوز إكس بي / ويندوز 7 / ويندوز 8		أنظمة التشغيل
بيوستار BIOSTAR تحتفظ بحق إضافة أو إزالة الدعم لأي نظام تشغيل مع أو بدون أنظار.		المدعومة

French

Spécifications	
Support Unité Centrale	Interface de connexion FM2+/FM2 pour série A AMD processeur Enveloppe thermique Unité Centrale maximum : 100Watt * Veuillez vous reporter à www.biostar.com.tw pour la liste des supports modèles d'Unité Centrale.
Jeu de puces	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Mémoire	Supporte mémoire DDR3 double canal 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) Banc de mémoire 2 x DDR3 DIMM, Supporte max. jusqu'à une mémoire de 32 GB Chaque module DIMM supporte module DDR3 non-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB * Veuillez vous reporter à www.biostar.com.tw pour la liste des soutien de la mémoire.
Stockage	AMD A88X/A78 FCH Supporte système RAID 0,1,10, 5 & AHCI (A88X FCH) Supporte système RAID 0,1,10 & AHCI (A78 FCH)
Réseau local	Realtek RTL 8111G 10/ 100/ 1000 Mb/s auto négociation, capacité bidirectionnelle à l'alternat / bidirectionnelle simultanée
Codec audio	ALC892 Canaux 7.1, écoute audio de haute définition
USB	AMD A88X/A78 FCH Port 6x USB 2.0 (2 sur les I/O arrières et 4 en interne) Port 4x USB 3.0 (2 sur les I/O arrières et 2 en interne)
Connecteur d'extension	2x Fente PCI 1x PCIe 2.0 x1 Fente 1x PCIe 3.0 x16 Fente
I/O arrières	1x PS/2 Clavier 1x PS/2 Souris 1x Port HDMI 1x Port VGA 1x Port DVI 1x port LAN 2x Port USB 2.0 2x Port USB 3.0 3x entrées audio

Spécifications		
I/O en interne	Hi-Fi A88S3E:	Hi-Fi A78S3E:
	8x Connecteur SATA 6.0Gb/s	6x Connecteur SATA 6.0Gb/s
	2x embases USB 2.0	2x embases USB 2.0
	1x embases USB 3.0	1x embases USB 3.0
	1x 4-Broche de carte	1x 4-Broche de carte
	1x 24-Broche de carte	1x 24-Broche de carte
	1x Connecteur ventilateur unité centrale	1x Connecteur ventilateur unité centrale
	2x Connecteur ventilateur système	2x Connecteur ventilateur système
	1x Fiche panneau avant	1x Fiche panneau avant
	1x Fiche audio avant	1x Fiche audio avant
	1x Fiche mémoire CMOS vide	1x Fiche mémoire CMOS vide
	1x Embase port imprimante	1x Embase port imprimante
	1x Embase port série	1x Embase port série
1x Connecteur sortie S/PDIF	1x Connecteur sortie S/PDIF	
1x Fiche Registre d'état Consommateur	1x Fiche Registre d'état Consommateur	
Facteur d'encombrement	Facteur d'encombrement microATX, 244 mm x 200 mm	
Support SE	Windows XP / 7 / 8 Biostar se réserve le droit d'ajouter ou d'enlever le support pour toute SE avec ou sans préavis.	

German

Spezifikationen	
CPU-Unterstützung	Anschluss-FM2+/FM2 für AMD A-Serie Prozessor Maximale CPU TDP (Thermal Design Power): 100 Watt * Bitte konsultieren Sie www.biostar.com.tw für CPU-Unterstützungsliste
Chipset	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Festplattenspeicher	Unterstützt zweikanaliges DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) 2 x DDR3 DIMM-SpeicherSlot, Max. Unterstützung bis zu 32 GB-Speicher Jedes DIMM unterstützt nicht-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3-Module * Bitte konsultieren Sie www.biostar.com.tw für Speicherunterstützung Liste.
Arbeitsspeicher	AMD A88X/A78 FCH Unterstützt RAID 0,1,10, 5 & AHCI (A88X FCH) Unterstützt RAID 0,1,10 & AHCI (A78 FCH)
LAN	Realtek RTL 8111G 10/ 100/ 1000 Mb Auto-Negotiation, Halb- / Voll-Duplex-fähig
Audio-Codec	ALC892 7.1 Kanäle, HD-Audio
USB	AMD A88X/A78 FCH: 6x USB 2.0-Port (2 hintere I/Os und 4 via interne Header) 4x USB 3.0-Port (2 hintere I/Os und 2 via interne Header)
Erweiterungsanschlüsse	2x PCI-Slot 1x PCIe 2.0 x1-Slot 1x PCIe 3.0 x16-Slot
Hintere I/Os	1x PS/2-Maus 1x PS/2-Keyboard 1x HDMI-Port 1x VGA-Port 1x DVI -Port 1x LAN-Port 2x USB 2.0-Port 2x USB 3.0-Port 3x Audio Jack

Spezifikationen		
Interne I/Os	Hi-Fi A88S3E:	Hi-Fi A78S3E:
	8x SATA 6.0Gb/s-Verbindung	6x SATA 6.0Gb/s-Verbindung
	2x USB 2.0-Header	2x USB 2.0-Header
	1x USB 3.0-Header	1x USB 3.0-Header
	1x 4-Pin-Stromverbindung	1x 4-Pin-Stromverbindung
	1x 24-Pin-Stromverbindung	1x 24-Pin-Stromverbindung
	1x CPU-Ventilatorverbindung	1x CPU-Ventilatorverbindung
	2x System-Ventilatorverbindung	2x System-Ventilatorverbindung
	1x Header für Frontpanel	1x Header für Frontpanel
	1x Header für Frontaudio	1x Header für Frontaudio
	1x Header für klares CMOS	1x Header für klares CMOS
	1x Header für Druckerport	1x Header für Druckerport
	1x Serieller Port-Header	1x Serieller Port-Header
	1x S/PDI-Auswurfsverbindung	1x S/PDI-Auswurfsverbindung
1x Consumer IR-Header	1x Consumer IR-Header	
Formfaktor	microATX Formfaktor, 244 mm x 200 mm	
OS-Unterstützung	Windows XP / 7 / 8 Biostar reserves the right to add or remove support for any OS with or without notice.	

Italian

Specificazioni	
Supporto processore	Slot FM2+/FM2 per processore AMD serie-A Alimentazione di Proiezione Termico (TDP - Thermal Design Power): 100Watt * Si prega di consultare www.biostar.com.tw per la lista di supporto del processore.
Tipo scheda	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Memoria	Supporta DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) Doppio Canale 2 x DDR3 DIMM Slot di Memoria Supporta fino a 32 GB Memoria Ogni DIMM supporta non-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3 moduli * Si prega di consultare www.biostar.com.tw per la lista di supporto del memoria.
Memorizzazione	AMD A88X/A78 FCH Supporta RAID 0,1,10, 5 & AHCI (A88X FCH) Supporta RAID 0,1,10 & AHCI (A78 FCH)
Catena	Realtek RTL 8111G 10/ 100/ 1000 Mb auto negoziazione, capacita di duplex Meta / Completo
Codec Audio	ALC892 Canali Audio di Alta Definizione 7.1
USB	Piattaforma AMD A88X/A78 FCH: Slot 6x USB 2.0 (2 nei ingressi/ uscite posteriore e 4 da distributori interni) Slot 4x USB 3.0 (2 nei ingressi/ uscite posteriore e 2 da distributori interni)
Slot di espansione	Slot 2x PCI Slot 1x PCIe 2.0 x1 Slot 1x PCIe 3.0 x16
Ingressi/ Uscite Posteriore	Mouse 1x PS/2 Tastiera 1x PS/2 Slot 1x HDMI Slot 1x VGA Slot 1x DVI Slot 1x LAN Slot 2x USB 2.0 Slot 2x USB 3.0 Jack audio 3x

Specificazioni		
Ingressi/ Uscite Interni	<p>Hi-Fi A88S3E:</p> <p>Connettore 8x SATA 6.0Gb/s</p> <p>Distributore 2x USB 2.0</p> <p>Distributore 1x USB 3.0</p> <p>Connettore con 4 pin x1</p> <p>Connettore con 24 pin x1</p> <p>Connettore Ventilatore processore x1</p> <p>Connettore Ventilatore Sistema x2</p> <p>Distributore Pannello Frontale x1</p> <p>Distributore Audio Frontale x1</p> <p>Distributore CMOS Diretto x1</p> <p>Distributore Slot Stampante x1</p> <p>Distributore Slot Serie x1</p> <p>Connettore esterno S/PDIF x1</p> <p>Distributore Consumabile IR x1</p>	<p>Hi-Fi A78S3E:</p> <p>Connettore 6x SATA 6.0Gb/s</p> <p>Distributore 2x USB 2.0</p> <p>Distributore 1x USB 3.0</p> <p>Connettore con 4 pin x1</p> <p>Connettore con 24 pin x1</p> <p>Connettore Ventilatore processore x1</p> <p>Connettore Ventilatore Sistema x2</p> <p>Distributore Pannello Frontale x1</p> <p>Distributore Audio Frontale x1</p> <p>Distributore CMOS Diretto x1</p> <p>Distributore Slot Stampante x1</p> <p>Distributore Slot Serie x1</p> <p>Connettore esterno S/PDIF x1</p> <p>Distributore Consumabile IR x1</p>
Fattore di Forma	Fattore di Forma microATX, 244 mm x 200 mm	
Supporto SO	<p>Windows XP / 7 / 8</p> <p>BioStar si riserva il diritto di aggiungere o ritirare il supporto per qualsiasi SO con o senza preavviso.</p>	

Japanese

仕様	
CPU サポート	AMD A-シリーズ プロセッサの Socket FM2+/FM2 最大 CPU TDP (Thermal Design Power 最大放熱量) :100 W *CPU サポート リストについては、 www.biostar.com.tw を参照してください。
チップセット	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
メモリ	デュアルチャンネル DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC) / 2600(OC) をサポート 2 x DDR3 DIMM メモリ スロット、最大 32 GB メモリまでサポート 各 DIMM は、非-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3 モジュールをサポートしています *サポートされているメモリのリストについては、 www.biostar.com.tw を参照してください。
保存スペース	AMD A88X/A78 FCH RAID 0,1,10, 5 & AHCI のサポート (A88X FCH) RAID 0,1,10 & AHCI のサポート (A78 FCH)
LAN	Realtek RTL 8111G 10/ 100/ 1000 Mb/s オートネゴシエーション、半/全 二重通信
オーディオ コーデック	ALC892 7.1 チャンネル、ハイ デフィニション オーディオ
USB	AMD A88X/A78 FCH: 6x USB 2.0 ポート (後部 I/O に2つ 及び 内蔵ヘッダー経由に4つ) 4x USB 3.0 ポート (後部 I/O に2つ 及び 内蔵ヘッダー経由に2つ)
拡張スロット	2x PCI スロット 1x PCIe 2.0 x1 スロット 1x PCIe 3.0 x16 スロット
後部 I/O	1x PS/2 キーボード 1x PS/2 マウス 1x HDMI ポート 1x VGA ポート 1x DVI ポート 1x LAN ポート 2x USB 2.0 ポート 2x USB 3.0 ポート 3x オーディオ ジャック

仕様		
内蔵 I/O	Hi-Fi A88S3E: 8x SATA 6.0Gb/s コネクタ 2x USB 2.0 ヘッダー 1x USB 3.0 ヘッダー 1x 4-Pin パワー コネクタ 1x 24-Pin パワー コネクタ 1x CPU ファン コネクタ 2x システム ファン コネクタ 1x フロント パネル ヘッダー 1x フロント オーディオ ヘッダー 1x クリア CMOS ヘッダー 1x プリンター ポート ヘッダー 1x シリアル ポート ヘッダー 1x S/PDIF アウト コネクタ 1x コンシューマー IR ヘッダー	Hi-Fi A78S3E: 6x SATA 6.0Gb/s コネクタ 2x USB 2.0 ヘッダー 1x USB 3.0 ヘッダー 1x 4-Pin パワー コネクタ 1x 24-Pin パワー コネクタ 1x CPU ファン コネクタ 2x システム ファン コネクタ 1x フロント パネル ヘッダー 1x フロント オーディオ ヘッダー 1x クリア CMOS ヘッダー 1x プリンター ポート ヘッダー 1x シリアル ポート ヘッダー 1x S/PDIF アウト コネクタ 1x コンシューマー IR ヘッダー
フォーム ファクタ	microATX フォーム ファクタ、244 mm x 200 mm	
サポート OS	Windows XP / 7 / 8 Biostar には、通知なしでサポート OS を変更する権限があります。	

Polish

Specyfikacje techniczne	
Obsługa procesora	Gniazdo procesora (Socket) FM2+/FM2 dla procesorów AMD seria-A Moc Wydzielanego Ciepła (TDP - Thermal Design Power): 100Watt * Proszę sprawdzić listę obsługiwanych procesorów na stronie internetowej www.biostar.com.tw
Rodzaj płyty	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Pamięć	Obsługa pamięci DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) Dwukanałowa 2 x DDR3 DIMM Pamięć Gniazda procesora (Slot), Maksymalna wielkość pamięci 32 GB Każdy DIMM obsługuje jeden moduł non-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3 * Proszę sprawdzić listę obsługiwanych pamięć na stronie internetowej www.biostar.com.tw
Przechowywanie	AMD A88X/A78 FCH Obsługa RAID 0,1,10, 5 & AHCI (A88X FCH) Obsługa RAID 0,1,10 & AHCI (A78 FCH)
LAN	Układ RTL 8111G 10/ 100/ 1000 Mb auto negocjacja, pojemność duplex Połowe / Pełny
Codec Audio	ALC892 Kanały Audio wysokiej Definicji 7.1
USB	Płyta AMD A88X/A78 FCH: 6 x złącza USB 2.0 (2 przez tylne porty wejścia/ wyjścia oraz 4 przez wewnętrzne porty) 4 x złącza USB 3.0 (2 przez tylne porty wejścia/ wyjścia oraz 2 przez wewnętrzne porty)
Złącza rozszerzeń	złącza 2x PCI (Slot) złącza 1x PCIe 2.0 x1 (Slot) złącza 1x PCIe 3.0 x16 (Slot)
Tylne porty wejścia/ wyjścia	Myszka 1x PS/2 Klawiatura 1x PS/2 Port 1x HDMI (gniazdo) Port 1x VGA Port 1x DVI Port 1x LAN Porty 2x USB 2.0 Porty 2x USB 3.0 Porty audio 3x

Specyfikacje techniczne		
Wewnętrzne porty wejścia/ wyjścia	Hi-Fi A88S3E:	Hi-Fi A78S3E:
	Złącza 8x SATA 6.0Gb/s	Złącza 6x SATA 6.0Gb/s
	Złącza 2x USB 2.0	Złącza 2x USB 2.0
	Złącza 1x USB 3.0	Złącza 1x USB 3.0
	Złącza 4 pionowe x 1	Złącza 4 pionowe x 1
	Złącza 24 pionowe x 1	Złącza 24 pionowe x 1
	Złącze wentylatora CPU x 1	Złącze wentylatora CPU x 1
	Złącze wentylatora obudowy x 2	Złącze wentylatora obudowy x 2
	Złącze przedniego panelu x1	Złącze przedniego panelu x1
	Złącze audio przedniego panelu x1	Złącze audio przedniego panelu x1
	Złącze bezpośrednie CMOS x1	Złącze bezpośrednie CMOS x1
	Złącze port drukarki x1	Złącze port drukarki x1
	Port szeregowy x1	Port szeregowy x1
	Port zewnętrzny S/PDIF x1	Port zewnętrzny S/PDIF x1
Złącze konsument IR x1	Złącze konsument IR x1	
Obudowa	Obudowa microATX, 244 mm x 200 mm	
Obsługa OS	Windows XP / 7 / 8 Biostar zastrzega sobie prawo do dodania lub wycofania obsługi dla OS, z wypowiedzeniem lub bez wypowiedzenia.	

Portuguese

Especificações	
Suporte Processador	Porta FM2+/FM2 para processador AMD série-A Alimentação de Design Térmico (TDP – Thermal Design Power): 100Watt * Por favor consulte www.biostar.com.tw para obter uma lista de suporte do processador.
Tipo Placa Mãe	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Memória	Suporta DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) Canal Duplo 2 x DDR3 DIMM Slot de memória Suporta até 32 GB Memória Cada DIMM suporta non-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3 módulo * Por favor consulte www.biostar.com.tw para obter uma lista de suporte do memória.
Armazenamento	AMD A88X/A78 FCH Suporta RAID 0,1,10, 5 & AHCI (A88X FCH) Suporta RAID 0,1,10 & AHCI (A78 FCH)
LAN	Realtek RTL 8111G 10/ 100/ 1000 Mb auto negociação, capacidade duplex Metade / Cheio
Codec de Audio	ALC892 Canais de Áudio de Alta Definição 7.1
USB	Plataforma AMD A88X/A78 FCH: Porta 6x USB 2.0 (2 nas entradas/saídas traseiras e 4 pelos Dispositivos internos) Porta 4x USB 3.0 (2 nas entradas/saídas traseiras e 2 pelos Dispositivos internos)
Slots de expansão	Porta 2x PCI Porta 1x PCIe 2.0 x1 Porta 1x PCIe 3.0 x16
Entradas/Saídas no painel traseiro	Mouse 1x PS/2 Teclado 1x PS/2 Porta 1x HDMI Porta 1x VGA Porta 1x DVI Porta 1x LAN Porta 2x USB 2.0 Porta 2x USB 3.0 Soquete audio 3x

Especificações		
Conectores na placa	Hi-Fi A88S3E:	Hi-Fi A78S3E:
	Conector 8x SATA 6.0Gb/s	Conector 6x SATA 6.0Gb/s
	Dispositivo 2x USB 2.0	Dispositivo 2x USB 2.0
	Dispositivo 1x USB 3.0	Dispositivo 1x USB 3.0
	Conector de 4 pinos x1	Conector de 4 pinos x1
	Conector de 24 pinos x1	Conector de 24 pinos x1
	Conector de Ventoinha processador x1	Conector de Ventoinha processador x1
	Conector de Ventoinha Sistema x2	Conector de Ventoinha Sistema x2
	Dispositivo Painel Frontal x1	Dispositivo Painel Frontal x1
	Dispositivo de Audio Frontal x1	Dispositivo de Audio Frontal x1
	Dispositivo CMOS Direct x1	Dispositivo CMOS Direct x1
	Dispositivo Porta Impressora x1	Dispositivo Porta Impressora x1
	Dispositivo Porta Série x1	Dispositivo Porta Série x1
Conector Externo S/PDIF x1	Conector Externo S/PDIF x1	
Dispositivo Consumível IR x1	Dispositivo Consumível IR x1	
Fator de Fôrma	Fator de Fôrma microATX, 244 mm x 200 mm	
Suporte OS	Windows XP / 7 / 8 Biostar reserva seu direito de adicionar ou retirar o suporte para qualquer OS com ou sem notificação.	

Russian

Спецификации	
Поддержка центрального процессора	Сокет FM2+/FM2 для процессоров AMD серии A Максимальный термопакет центрального процессора (TDP): 100 ватт * Перечень поддержки центрального процессора смотрите на www.biostar.com.tw .
Набор микросхем	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Память	Поддерживает двухканальный DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) 2 гнезда платы памяти DDR3 DIMM, максимальная память до 32 Гб Каждый модуль DIMM поддерживает модуль не-ECC 512 Мб/ 1/ 2/ 4/ 8/ 16 Гб DDR3 * Перечень поддержки памяти смотрите на www.biostar.com.tw .
Накопитель	AMD A88X/A78 FCH Поддерживает RAID 0,1,10, 5 & AHCI (A88X FCH) Поддерживает RAID 0,1,10 & AHCI (A78 FCH)
Локальная сеть	Realtek RTL 8111G Автоогласование 10/ 100/ 1000 Мб/с, работает в полно/полудуплексном режиме
Аудиокодек	ALC892 Каналы 7.1, высококачественное аудио
USB	AMD A88X/A78 FCH: 6 портов USB 2.0 (2 сзади ввода-вывода и 4 через внутренние контакты) 4 портов USB 3.0 (2 сзади ввода-вывода и 2 через внутренние контакты)
Гнезда расшир.	2x гнезда PCI 1x PCIe 2.0 x1 гнездо 1x PCIe 3.0 x16 гнездо
Задняя плата ввода-вывода	1 мышь PS/2 1 клавиатура PS/2 1 порт HDMI 1 порт VGA 1 порт DVI 1 порт локальной сети 2 порта USB 2.0 2 порта USB 3.0 3 гнезд для подключения наушников

Спецификации		
Внутр. Плата ввода-вывода	Hi-Fi A88S3E:	Hi-Fi A78S3E:
	Соединитель 8x SATA 6 Гб/с	Соединитель 6x SATA 6 Гб/с
	2 контакта USB 2.0	2 контакта USB 2.0
	1 контакта USB 3.0	1 контакта USB 3.0
	1 4-выводный разъем питания	1 4-выводный разъем питания
	1 24-выводный разъем питания	1 24-выводный разъем питания
	1 разъем вентилятора ЦП	1 разъем вентилятора ЦП
	2 разъема вентилятора системы	2 разъема вентилятора системы
	1 контакт передней панели	1 контакт передней панели
	1 контакт передней аудиопанели	1 контакт передней аудиопанели
	1 контакт микросхемы Clear CMOS	1 контакт микросхемы Clear CMOS
	1 контакт порта принтера	1 контакт порта принтера
	1 инфракрасный пользовательский контакт	1 инфракрасный пользовательский контакт
	1 контакт последовательного порта	1 контакт последовательного порта
	1 соединитель S/PDIF-Out	1 соединитель S/PDIF-Out
1 инфракрасный пользовательский контакт	1 инфракрасный пользовательский контакт	
Конструктив	Форм-фактор microATX, 244 мм x 200 мм	
Поддержка ОС	Windows XP / 7 / 8 Biostar оставляет за собой право добавлять или удалять поддержку любой ОС, с уведомлением или без.	

Spanish

Especificaciones	
Compatibilidad con el procesador	Ranura FM2+/FM2 para procesador AMD serie - A Alimentación de Proyección Térmica (TDP – Thermal Design Power): 100Watt *Por favor consultar con www.biostar.com.tw para la lista de compatibilidad con el procesador.
Tipo de Placa	AMD A88X FCH (Hi-Fi A88S3E) AMD A78 FCH (Hi-Fi A78S3E)
Memoria	Soporta DDR3 800/ 1066/ 1333/ 1600/ 1866/ 2133/ 2400(OC)/ 2600(OC) Doble Canal 2x DDR3 DIMM Ranura de memoria Soporta hasta 32 GB Memoria Cada DIMM soporta un modulo non-ECC 512MB/ 1/ 2/ 4/ 8/ 16 GB DDR3 *Por favor consultar con www.biostar.com.tw para la lista de compatibilidad con el memoria.
Almacenamiento de información	AMD A88X/A78 FCH Soporta RAID 0,1,10, 5 & AHCI (A88X FCH) Soporta RAID 0,1,10 & AHCI (A78 FCH)
LAN	Realtek RTL 8111G 10/ 100/ 1000 Mb/s auto negociación, capacidad dúplex Mitad/Completo
Códec Audio	ALC892 Canales Audio de Alta Definición 7.1
USB	Plataforma AMD A88X/A78 FCH: Ranura 6x USB 2.0 (2 en las entradas/salidas posteriores y 4 por los distribuidores internos) Ranura 4x USB 3.0 (2 en las entradas/salidas posteriores y 2 por los distribuidores internos)
Ranuras de Extinción	Ranura 2x PCI Ranura 1x PCIe 2.0 x1 Ranura 1x PCIe 3.0 x16
Panel trasero de E/S	Ratón 1x PS/2 Teclado 1x PS/2 Ranura 1x HDMI Ranura 1x VGA Ranura 1x DVI Ranura 1x LAN Ranura 2x USB 2.0 Ranura 2x USB 3.0 Socket audio 3x

Especificaciones		
Conectores en placa	Hi-Fi A88S3E:	Hi-Fi A78S3E:
	Conector 8x SATA 6Gb's	Conector 6x SATA 6Gb's
	Distribuidor 2x USB 2.0	Distribuidor 2x USB 2.0
	Distribuidor 1x USB 3.0	Distribuidor 1x USB 3.0
	Conector con 4 patillas x1	Conector con 4 patillas x1
	Conector con 24 patillas x1	Conector con 24 patillas x1
	Conector Ventilador procesador x1	Conector Ventilador procesador x1
	Conector Ventilador Sistema x2	Conector Ventilador Sistema x2
	Distribuidor Panel Frontal x1	Distribuidor Panel Frontal x1
	Distribuidor Audio Frontal x1	Distribuidor Audio Frontal x1
	Distribuidor CMOS Directo x1	Distribuidor CMOS Directo x1
	Distribuidor Ranura Impresora x1	Distribuidor Ranura Impresora x1
	Distribuidor Ranura Serie x1	Distribuidor Ranura Serie x1
	Conector Externo S/PDIF x1	Conector Externo S/PDIF x1
Distribuidor Consumible IR x1	Distribuidor Consumible IR x1	
Factor de Forma	Factor de Forma microATX, 244 mm x 200 mm	
Soporte OS	Windows XP / 7 / 8 Biostar reserva su derecho de añadir o retirar el soporte para cada OS con o sin notificación.	

2013/09/18